


OpenGear Converter Audio to SDI



Includes everything you need to embed 4 channels of analog audio or 8 channels of AES/EBU digital audio into any SDI video connection. Embed audio from audio mixers and analog decks into SDI video for use with SDI routers and decks, or to add extra audio channels to video converters!

\$495

Connections

SDI Video Input

Switchable between SD, HD and 3Gb/s SDI.

SDI Video Output

Automatically matches the SD, HD and 3Gb/s SDI video input.

Analog Audio

4 channels of professional balanced analog audio with openGear™ standard 3 pin connections.

AES/EBU Digital Audio

8 channels of professional balanced digital with openGear™ standard 3 pin connections.

SDI Redundant Input

Automatically switches over if main SDI input is lost.

Multi Rate Support


Auto detection of SD, HD and Level B 3 Gb/s SDI inputs.

Updates and Configuration

Via USB 2.0 high speed. (480 Mb/s)

Reclocking

Yes



Standards

SDI Compliance

SMPTE 292M, SMPTE 259M, SMPTE 296M, ITU-R BT.656 and ITU-R BT.601.

SDI Video Rates

SDI video connections are switchable between standard definition and high definition.

SDI Video Sampling

4:2:2

SDI Audio Sampling

Television standard sample rate of 48 kHz and 24-bit.

SDI Color Precision

4:2:2

SDI Color Space

YUV

SDI Auto Switching

Automatically selects between SD-SDI, HD-SDI and 3 Gb/s SDI.

SDI Format Support

625/25 PAL, 525/29.97 NTSC, 1080PsF23.98, 1080PsF24, 1080PsF25, 1080i50, 1080i59.94, 1080i60, 720p50, 720p59.94 and 720p60.

Software

Software Control

Mac OS X™ and Windows™ software upgrade via USB.

Internal Software Upgrade

Via included updater application.

Operating Systems



Mac OS X 10.10 Yosemite,
Mac OS X 10.11 El Capitan
or later.




Windows 8.1 or
Windows 10.

Settings Control

OpenGear DashBoard network control software, Mini Switches or USB software.

Physical Specifications



Environmental Specifications

Operating Temperature

0° to 40° C (32° to 104° F)

Storage Temperature

-20° to 45° C (-4° to 113° F)

Relative Humidity

0% to 90% non-condensing

What's Included

OpenGear Converter Audio to SDI

Warranty

3 Year Limited Manufacturer's Warranty.

All items on this website are copyright Blackmagic Design Pty. Ltd. 2016, all rights reserved.
All trademarks are property of their respective owners. MSRP excludes sales taxes/duties and shipping costs.

Blackmagic Design Authorized Reseller