

Blackmagic Studio Camera 4K Plus



£975

The Blackmagic Studio Camera 4K Plus has been specifically designed as the perfect camera for ATEM Mini. It's the same high quality broadcast camera, but the HDMI centric design removes all the expensive broadcast connections so it's much lower cost. The HDMI is incredibly powerful as it connects video to the ATEM Mini, while at the same time camera control, tally and the remote record trigger is sent to the camera using the same HDMI connection. That makes it very fast to set up for a job.

Camera Features

Effective Sensor Size

17.78mm x 10mm (Four Thirds)

Signal to Noise Ratio

63dB for 2160p.

Screen Type

LCD capacitive touchscreen.

Lens Mount

Active MFT Mount.

Shooting Resolutions

3840 x 2160 (Ultra HD) up to 60 fps.

Screen Brightness

600 nits

Lens Control

Iris, focus, zoom on supported lenses.

Frame Rates

23.98, 24, 25, 29.97, 30, 50, 59.94 and 60 frames per second.

Controls

Touchscreen camera settings and menus with rotary settings dial, program button, F1, F2 and F3 assignable function buttons, brightness contrast and peaking dials.

Dynamic Range

13 Stops.

Off-speed frame rates up to 60 fps in Ultra HD.

Dual Native ISO

0dB and 18dB gain.

Focus

Auto focus available using compatible lenses.

Mounting Options

2 x 1/4 inch tripod mount.
1 x 3/8 inch tripod mount.

Sensitivity at 0dB Gain

f11 with 2160p59.94.

f12 with 2160p50.

at 2,000 lux with 89.9% reflectance.

Screen Dimensions

7 inch 1920 x 1200

Connections

HDMI 2.0 Video Outputs

1

Analog Audio Input

1 x 3.5mm Stereo Input. Can also be used for Timecode input.

Analog Audio Output


1 x 3.5mm mini jack for headphones.

Remote Control

Remote camera control over HDMI.

Computer Interface

2 x USB Type-C 3.1 Gen 1 (up to 5Gb/s) expansion ports for external recording and focus / zoom demand connection. Software updates using USB-C Port A.



Audio

Microphone

Integrated stereo microphone.

Built in Speaker

1 x mono speaker.

Standards

SD Video Standards

None

HD Video Standards

1080p23.98, 1080p24, 1080p25,
1080p29.97, 1080p30, 1080p50,
1080p59.94, 1080p60

Ultra HD Video Standards

2160p23.98, 2160p24, 2160p25,
2160p29.97, 2160p30, 2160p50,
2160p59.94, 2160p60

HDMI Audio Sampling

Television standard sample rate of 48 kHz and 24-bit.

Media

Media

2 x USB-C 3.1 Gen 1 expansion ports for external media for recording Blackmagic RAW.

Media Format

Can format media to ExFAT (Windows/Mac) or HFS+ (Mac) file systems.

Supported Codecs

Codecs

Blackmagic RAW Constant Bitrate 3:1,
Blackmagic RAW Constant Bitrate 5:1,
Blackmagic RAW Constant Bitrate 8:1,
Blackmagic RAW Constant Bitrate 12:1,
Blackmagic RAW Constant Quality Q0,
Blackmagic RAW Constant Quality Q1,
Blackmagic RAW Constant Quality Q3,
Blackmagic RAW Constant Quality Q5

Storage Features

Storage Type

2 x USB-C 3.1 Gen 1 expansion ports for external media.

Recording Formats

Blackmagic RAW 3:1, 5:1, 8:1, 12:1, Q0, Q1, Q3 and Q5 in Ultra HD 3840 x 2160 at the selected frame rate.

Storage Rates

Storage rates based on 30 frames per second.

3840 x 2160 (Ultra HD)

Blackmagic RAW 3:1 - 127 MB/s

Blackmagic RAW 5:1 - 77 MB/s

Blackmagic RAW 8:1 - 48 MB/s

Blackmagic RAW 12:1 - 32 MB/s

Blackmagic RAW Q0 - 96 to 190 MB/s

Blackmagic RAW Q1 - 64 to 153 MB/s

Blackmagic RAW Q3 - 43 to 109 MB/s

Blackmagic RAW Q5 - 26 to 64 MB/s

Constant Quality storage rates quoted are indicative only.

Actual storage rates are entirely dependent on image subject matter.

Control

External Control

Blackmagic Zoom Demand and Blackmagic Focus Demand for controlling your camera and lens from tripod handles.

Blackmagic Control Protocol over HDMI for external control when used with a compatible ATEM switcher with ATEM Software Control or ATEM Advanced Panel. Includes control of some camera settings, focus, iris and zoom with compatible lenses, color corrector, tally and record start and stop to external media via USB expansion port.

Color Corrector

DaVinci YRGB

Tally

Live Tally Indicator

1 x front facing for talent,

1 x rear facing for operator.

Software

Software Included

Blackmagic Camera Setup for Mac and Windows.

Operating Systems



Mac 10.15 Catalina,
Mac 11.1 Big Sur or later.



Windows 10, 64-bit.

Power Requirements

Power Supply

1 x External 12V DC 60W power supply.

Power Inputs

1 x 12V DC locking 5.5 mm barrel connector.

Power Usage

26 - 40 W.

Optional Accessories

Blackmagic Focus Demand

Blackmagic Zoom Demand

ATEM Mini switchers

ATEM Television Studio HD and

HD Pro switchers

Blackmagic 3G-SDI Shield for Arduino

Physical Specifications



Environmental Specifications

Operating Temperature

0° to 40° C (32° to 104° F)

Storage Temperature

-20° to 45° C (-4° to 113° F)

Relative Humidity

0% to 90% non-condensing

What's Included

Blackmagic Studio Camera 4K Plus

Blackmagic Studio Camera Sun Shade

Tripod Mount compatible with 15mm lightweight rails

Turret Dust Cap

External 12V DC power supply with locking connector and international sockets adapters for most countries.

Warranty

12 Month Limited Manufacturer's Warranty.

All items on this website are copyright Blackmagic Design Pty. Ltd. 2021, all rights reserved.
All trademarks are property of their respective owners. MSRP excludes VAT and local shipping costs.
This website uses remarketing services to advertise on third party websites to previous visitors to our site.
You can opt out at any time by changing cookie settings. [Privacy Policy](#)

Blackmagic Design Authorized Reseller