

# OpenGear Converter Optical Fiber



Convert SDI to Optical Fiber, and Optical Fiber to SDI simultaneously. Blackmagic OpenGear Optical Fiber auto switches between any SD, HD, 3G HD-SDI video standards and each direction is completely independent.

\$495

## Connections

#### **SDI Video Input**

Switchable between SD, HD and 3 Gb/s SDI.

#### **SDI Video Output**

Automatically matches the SD, HD and 3 Gb/s SDI Input.

#### **Optical Fiber Video Input**

1 x 10-bit SD/HD/3 Gb/s SDI switchable.

#### **Optical Fiber Video Output**

1 x 10-bit SD/HD/3 Gb/s SDI switchable.

# Optical Fiber Audio Input

16 channel embedded.

#### **Optical Fiber Audio Output**

16 channel embedded.

#### Multi Rate Support

Auto detection of SD, HD and Level B 3 Gb/s SDI inputs.

#### **Updates and Configuration**

Via USB 2.0 high speed. (480 Mb/s)

#### Reclocking

Yes



# Standards

## **SDI Compliance**

SMPTE 292M, SMPTE 259M, SMPTE 296M, ITU-R BT.656, ITU-R BT.601 and SMPTE 297M for Optical Fiber SDI.

#### **SDI Video Rates**

SDI video connections are switchable between standard definition and high definition.

## **SDI Video Sampling**

4:2:2

#### **SDI Audio Sampling**

Television standard sample rate of 48 kHz and 24-bit.

#### **SDI Color Precision**

4:2:2

#### **SDI Color Space**

YUV

## **SDI Auto Switching**

Automatically selects between SD, HD and 3 Gb/s SDI.

#### **ASI Support**

Yes

## **SDI Format Support**

625/25 PAL, 525/29.97 NTSC, 1080PsF23.98, 1080PsF24, 1080PsF25, 1080i50, 1080i59.94, 1080i60, 720p50, 720p59.94 and 720p60.

# Software

## **Software Control**

Dashboard

# **Operating Systems**



Mac OS X 10.10 Yosemite, Mac OS X 10.11 El Capitan or later.




Windows 8.1 or Windows 10.

# Settings Control

OpenGear DashBoard network control software.

# **Physical Specifications**



# **Environmental Specifications**

# Operating Temperature

0° to 40° C (32° to 104° F)

## Storage Temperature -20° to 45° C (-4° to 113° F)

# **Relative Humidity** 0% to 90% non-condensing

# What's Included

OpenGear Converter Optical Fiber

# Warranty

3 Year Limited Manufacturer's Warranty.

lackmagic [	Design Autho	orized Reselle	er				